Technical Data Sheet

1206 Package Chip Infrared LED With Inner Lens

Features

- High reliability
- Small double-end package
- Peak wavelength λ p=850nm
- Package in 8mm tape on 7" diameter reel
- Low forward voltage
- Pb free
- The product itself will remain within RoHS compliant version.

Descriptions

HIR11-21C/L11/TR8 is an infrared emitting diode in miniature SMD package which is molded in a water clear plastic With flat top view lens. The device is spectrally matched with silicon photodiode


and phototransistor.

Applications

- PCB mounted infrared sensor
- Infrared remote control units with high power requirement
- Smoke detector
- Infrared applied system

Device Selection Guide

LED Part No.	Chip Material	Lens Color	
HIR	GaAlAs	Water clear	




http://www.everlight.com Prepared date : 07-20-2005



HIR11-21C/L11/TR8



Package Dimensions



Notes: 1.All dimensions are in millimeters 2.Tolerances unless dimensions ±0.1mm

Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Rating	Units
Continuous Forward Current	$I_{\rm F}$	65	mA
Peak Forward Current	I _{FP}	1.0	А
Reverse Voltage	V _R	5	V
Operating Temperature	T _{opr}	-25 ~ +85	°C
Storage Temperature	T _{stg}	-40 ~ +85	°C
Soldering Temperature	T_{sol}	260	°C
Power Dissipation at(or below)	P_d	130	mW
25℃ Free Air Temperature			

Notes: *1:I_{FP} Conditions--Pulse Width \leq 100 μ s and Duty \leq 1%.

*2:Soldering time \leq 5 seconds.

http:\\www.everlight.com Prepared date : 07-20-2005



Electro-Optical Characteristics (Ta=25°C)

Parameter	Symbol	Condition	Min.	Typ.	Max.	Units	
		I _F =20mA	1.0	2.0			
Radiant Intensity	Ee	. $I_F\!\!=\!\!100mA$ Pulse Width $\!\leq\!100\mus$,Duty $\!\leq\!1\%$		10		mW /sr	
Peak Wavelength	λp	I _F =20mA		850		nm	
Spectral Bandwidth	Δλ	I _F =50mA		45		nm	
	age V _F	I _F =20mA		1.45	1.65		
Forward Voltage		. $I_F\!\!=\!\!100mA$ Pulse Width $\!\leq\!100\mus$,Duty $\!\leq\!1\%$		1.80	2.40	V	
Reverse Current	I _R	V _R =5V			10	μA	
View Angle	2 0 1/2	I _F =20mA		75		deg	

http://www.everlight.com Prepared date : 07-20-2005




Typical Electro-Optical Characteristics Curves

Fig.1 Forward Current vs.

Fig.2 Spectral Distribution

Ambient Temperature



Everlight Electronics Co., Ltd. Device No : DTH-011-001 http://www.everlight.com Prepared date : 07-20-2005 Rev 2 Page: 4 of 10 Prepared by : Jaine Tsai



 20°

 30°


 40°

 50°

 60°

 70° 80°

Typical Electro-Optical Characteristics Curves



100

120

Everlight Electronics Co., Ltd. Device No: DTH-011-001

50

75

Ambient Temperature(° C)

25

http://www.everlight.com Prepared date : 07-20-2005

25

50

75

Ambient Temperature(° C)

Rev 2 Page: 5 of 10 Prepared by : Jaine Tsai

100

120




Precautions For Use

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

- 2. Storage
 - 2.1 Do not open moisture proof bag before the products are ready to use.
- 2.2 Before opening the package, the LEDs should be kept at 30° C or less and 90% RH or less.
- 2.3 The LEDs should be used within a year.
- 2.4 After opening the package, the LEDs should be kept at 30° C or less and 70% RH or less.
- 2.5 The LEDs should be used within 168 hours (7 days) after opening the package.
- 2.6 If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions.
 Baking treatment : 60±5°C for 24 hours.
- 3. Soldering Condition
- 3.1 Pb-free solder temperature profile



- 3.2 Reflow soldering should not be done more than two times.
- 3.3 When soldering, do not put stress on the LEDs during heating.
- 3.4 After soldering, do not warp the circuit board.

http://www.everlight.com Prepared date : 07-20-2005




4.Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than 280° C for 3 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.





Reliability Test Item And Condition


The reliability of products shall be satisfied with items listed below. Confidence level : 90%

LTPD: 10%


NO.	Item	Test Conditions	Test Hours/	Sample	Failure	Ac/Re
			Cycles	Sizes	Judgement	
					Criteria	
1	REFLOW Soldering	TEMP. $: 260^{\circ}C \pm 5^{\circ}C$	6Mins	22pcs		0/1
		5secs			$I_R \ge U \times 2$	
2	Temperature Cycle	H : +100°C 15mins	50Cycles	22pcs	$Ee \leq Lx0.8$	0/1
		5mins	-		$V_F \ge U x 1.2$	
		$L:-40^{\circ}C$ 15mins				
3	Thermal Shock	H :+100°C ▲ 5mins	50Cycles	22pcs	U : Upper	0/1
		▼ 10secs	-		Specification	
		$L:-10^{\circ}C$ 5mins			Limit	
4	High Temperature	TEMP. ∶ +100°C	1000hrs	22pcs	L: Lower	0/1
	Storage				Specification	
5	Low Temperature	ТЕМР. : -40°С	1000hrs	22pcs	Limit	0/1
	Storage					
6	DC Operating Life	I _F =20mA	1000hrs	22pcs		0/1
7	High Temperature/	85°C / 85% R.H	1000hrs	22pcs		0/1
	High Humidity					



Package Dimensions



Taping Dimensions



Everlight Electronics Co., Ltd. Device No : DTH-011-001 http://www.everlight.com Prepared date : 07-20-2005 Rev 2Page: 9 of 10Prepared by : Jaine Tsai



Packing Quantity Specification

 $1.2000 Pcs/1 Volume \ , \ 1 Volume/1 Bag$

2.10Boxes/1Carton

Label Form Specification



CPN: Customer's Production Number P/N : Production Number QTY: Packing Quantity CAT: Ranks HUE: Peak Wavelength REF: Reference LOT No: Lot Number MADE IN TAIWAN: Production Place

Notes

- 1. Above specification may be changed without notice. EVERLIGHT will reserve authority on material change for above specification.
- 2. When using this product, please observe the absolute maximum ratings and the instructions for using outlined in these specification sheets. EVERLIGHT assumes no responsibility for any damage resulting from use of the product which does not comply with the absolute maximum ratings and the instructions included in these specification sheets.
- 3. These specification sheets include materials protected under copyright of EVERLIGHT corporation. Please don't reproduce or cause anyone to reproduce them without EVERLIGHT's consent.

EVERLIGHT ELECTRONICS CO., LTD. Office: No 25, Lane 76, Sec 3, Chung Yang Rd, Tucheng, Taipei 236, Taiwan, R.O.C *Tel:* 886-2-2267-2000, 2267-9936 *Fax:* 886-2267-6244, 2267-6189, 2267-6306 *http:*\\www.everlight.com

Everlight Electronics Co., Ltd. Device No : DTH-011-001 http://www.everlight.com Prepared date : 07-20-2005 Rev 2Page: 10 of 10Prepared by : Jaine Tsai